

## DS-PKA-WLM Wireless Keypad

The DS-PKA-WLM series wireless keypad can connect to security control panel for alarm control and operation. It can also notice alarm by indicator and buzzer.



### Available Models

- DS-PKA-WLM-433 (White)
- DS-PKA-WLM-433 (Black)
- DS-PKA-WLM-868 (White)
- DS-PKA-WLM-868 (Black)

### Features

- 433/868 MHz two-way wireless communication
- AES-128 encryption
- Operation: Arming, disarming, alarm clearing, etc.
- Arming or disarming with card
- Patrol card (different from the arming/disarming card) checking in
- Full touch screen design with LED backlight



## Specifications

Model		DS-PKA-WLM-433	S-PKA-WLM-868
RF	RF speed	10.0 kbps/4.8 bps	
	RF frequency	433 MHz/868 MHz	
	RF modulation	2GFSK	
	RF distance	800 m (open area)	
	RF power	10 dBm	
Interface & component	TAMPER switch	1	
	RF module	Communicates with wireless control panel	
	Card	Supports standard IC card swiping	
	Buzzer	1	
	Serial port	1, reserved	
	Numeric	10 keys: 0 to 9	
	Function key	6 function keys: fire alarm, away arming, stay arming, disarming, delete, and confirm	
Application & protocol	Protocol	HIK wireless protocol: Access to wireless control panel, two-way communication	
Electrical & battery	Power	3 VDC power input	
	Battery type	4 AA batteries	
	Battery life span	3 years	
Others	Operation humidity	10% to 90% (No condensing)	
	Operation temperature	-10 °C to +55 °C (-4 °F to +122 °F)	
	Color	White or black	
	Dimension	φ131.5 mm (5.2"); height: 23 mm (0.9")	

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7652-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-87-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com