

## DS-PTA-WL-433/DS-PTA-WL-868 Wireless Tag Reader

DS-PTA-WL wireless tag reader can connect to wireless security control panel for arming/disarming. It can also notice alarm by indicator and buzzer.



### Available Model

- DS-PTA-WL-433 (White)
- DS-PTA-WL-433 (Black)
- DS-PTA-WL-868 (White)
- DS-PTA-WL-868 (Black)

### Key Feature

- 433/868MHz two-way wireless communication
- AES-128 encryption
- Operation: Stay arming (hold for 3 s), away arming (hold < 1 s), disarming (hold < 1 s)
- Patrol card (different from the arming/disarming card) checking in
- Front and rear panel tamper-proof
- Protection level: IP65
- Outdoor installation



## Specification

Model		DS-PTA-WL Wireless Tag Reader
Wireless module	RF speed	10.0kbps/4.8kbps
	RF method	Two way communication
	RF encryption	AES-128
	RF frequency	433/868 MHz
	RF distance	800 m (open area)
	RF power	10 dBm
Interface & component	Sensor	1 RFID
	TAMPER switch	1
	Indicator	3, red, green and orange
	Buzzer	Prompt for card operation and tampering alarm
Electrical & battery	Power	3 VDC power input
	Battery type	4 AAA batteries
	Battery life span	5 years in stand-by status
Others	Operation humidity	10% to 90% (no condensing)
	Operation temperature	-20°C to +60°C (-4°F to +140°F)
	Dimension (W × H × D)	90.78 mm × 90.78 mm × 15.5 mm (3.57" × 3.57" × 0.61")
	Color	Black and white
	Protection level	IP65
	Installation	Wall mounting

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7652-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-87-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com