



Model: **TX500K02**

Specifications:	
Radio Brand	KENWOOD
Radio Model	TK-280/290/380/385/390/480/481/2041/21 40/3140/3148/218 0/3180,NX200/300
Speaker Specification:	
Type	Transducer Moving coil dynamic speaker
Impedance	90Ω±15% @1KHZ
Sensitivity	120±3dB @1KHZ
Frequency respond	F0~9KHz
Rated input power	500mW
Maximum input power	1000mW
Microphone Specification	
Sensitivity Range	-63± 3dB RL=1.0K Ω Vs=2.0V(DC) 1KHz
Impedance Max	2.2KΩ 1kHz (RL=2.2KΩ)
Frequency	20-20KHz
Current Consumption Max	0.5uA RL=2.2KΩ Vs=3.0V(DC)
Operation Voltage Range	2.5-10V (DC)
Max Sound pressure Level	108dB S. P. L